

Datenblatt / Technical Data

Verstärker / Amplifier — Hydrogen Series



Model	GZHA 2250XII
Power WRMS @ 4 / 2 Ohm (14,4 V, 1% THD)	2 x 145 / 225
Power WRMS @ 2 Ohm (14,4 V, 10% THD)	2 x 300
Power WRMS @ 4 Ohm gebrückt / bridged	1 x 600
Highpass	5 - 500Hz
Lowpass	30 - 250Hz
Subsonic Filter	5 - 250Hz
Phaseshift	0 - 180°
Bandpass	5 - 250Hz
Bass Boost 45Hz	0 - 12dB
RCA (stereo)	1 x In
Maße / Dimensions	30,3 x 6,1 x 30 cm / 11.9" x 2.4" x 11.8"
Doppel Netzteil / Dual power supply	
Bass Fernbedienung mit 5 m Kabel / Bass remote incl. 16.4' cable	




Model	GZHA 2350XII
Power WRMS @ 4 / 2 Ohm (14,4 V, 1% THD)	2 x 240 / 430
Power WRMS @ 1 Ohm (14,4 V, 10% THD)	2 x 700
Power WRMS @ 2 Ohm gebrückt / bridged	1 x 1500
Highpass	5 - 500Hz
Lowpass	30 - 250Hz
Subsonic Filter	5 - 250Hz
Phaseshift	0 - 180°
Bandpass	5 - 250Hz
Bass Boost	0 - 12dB (30 - 50Hz)
RCA (stereo)	1 x In
Maße / Dimensions	30,3 x 6,1 x 40 cm / 11.9" x 2.4" x 15.7"
Doppel Netzteil / Dual power supply	
Bass Fernbedienung mit 5 m Kabel / Bass remote incl. 16.4' cable	

Ground Zero GmbH

Erlenweg 25, 85658 Eggenheim, Germany
Tel 08095 873 830, Fax 08095 873 8310
www.ground-zero-audio.com

Ground Zero, Radioactive, Hydrogen, Uranium,
Nuclear, Plutonium and Titanium are audio trade-
marks of Ground Zero GmbH, Germany.



Datenblatt / Technical Data

Verstärker / Amplifier — Hydrogen Series



Model	GZHA 4120XII
Power WRMS @ 4 / 2 Ohm (14,4 V, 1% THD)	4 x 75 / 100
Power WRMS @ 2 Ohm (14,4 V, 10% THD)	4 x 125
Highpass	40 - 3000HZ (Ch 1+2) 5 - 250Hz (Ch 3+4)
Lowpass	80 Hz Switch (Ch 1+2) 30 - 250Hz (Ch 3+4)
Subsonic Filter	5 - 250Hz (Ch 3+4)
Phaseshift	0 - 180°
Bandpass	5 - 250Hz (Ch 3+4)
RCA (stereo)	2 x In / 1 x Out
Maße / Dimensions	30,3 x 6,1 x 28 cm / 11.9" x 2.4" x 11"
Doppel Netzteil / Dual power supply	
Bass Fernbedienung mit 5 m Kabel / Bass remote incl. 16.4' cable	



Model	GZHA 4150XII
Power WRMS @ 4 / 2 Ohm (14,4 V, 1% THD)	4 x 85 / 115
Power WRMS @ 2 Ohm (14,4 V, 10% THD)	4 x 140
Highpass	40 - 3000HZ (Ch 1+2) 5 - 250Hz (Ch 3+4)
Lowpass	80 Hz Switch (Ch 1+2) 30 - 250Hz (Ch 3+4)
Subsonic Filter	5 - 250Hz (Ch 3+4)
Phaseshift	0 - 180° (Ch 3+4)
Bass Boost 45Hz	0 - 12dB (Ch 3+4)
Bandpass	5 - 250Hz (Ch 3+4)
RCA (stereo)	2 x In / 1 x Out
Maße / Dimensions	30,3 x 6,1 x 30 cm / 11.9" x 2.4" x 11.8"
Doppel Netzteil / Dual power supply	
Bass Fernbedienung mit 5 m Kabel / Bass remote incl. 16.4' cable	

Ground Zero GmbH

Erlenweg 25, 85658 Eggenheim, Germany
Tel 08095 873 830, Fax 08095 873 8310
www.ground-zero-audio.com

Ground Zero, Radioactive, Hydrogen, Uranium,
Nuclear, Plutonium and Titanium are audio trade-
marks of Ground Zero GmbH, Germany.



Datenblatt / Technical Data

Verstärker / Amplifier — Hydrogen Series



Model	GZHA 5125XII
Power WRMS @ 4 / 2 Ohm (14,4 V, 1% THD)	4 x 75 / 100 + 1 x 250 / 370
Power WRMS @ 2 Ohm (14,4 V, 10% THD)	4 x 140 + 1 x 500
Highpass	80Hz Switch (Ch 1+2) 40 - 3000HZ (Ch 3+4)
Lowpass	30 - 250Hz (Ch 5)
Subsonic Filter	5 - 50Hz (Ch 5)
Phaseshift	0 - 180° (Ch 3+4)
RCA (stereo)	3 x In
Maße / Dimensions	30,3 x 6,1 x 50 cm / 11.9" x 2.4" x 19.7"
Doppel Netzteil / Dual power supply	
Bass Fernbedienung mit 5 m Kabel / Bass remote incl. 16.4' cable	

Wir behalten uns das Recht vor, zukünftig nötige Änderungen oder Verbesserungen an dem Produkt vorzunehmen ohne den Kunden darüber zu informieren.

We reserve the right to make needed change or improvement to the product without informing customer about this in advance.

Ground Zero GmbH

Erlenweg 25, 85658 Eggenstein, Germany
Tel 08095 873 830, Fax 08095 873 8310
www.ground-zero-audio.com

Ground Zero, Radioactive, Hydrogen, Uranium,
Nuclear, Plutonium and Titanium are audio trade-
marks of Ground Zero GmbH, Germany.

